

CNet is proud to introduce CFC-20TM media converter providing the simplest way to interconnect any copper 10/100 TP port to fiber 100BASE-FX interface. CFC-20TM smoothly transfers data between RJ-45 and 100BASE-FX Multi-Mode ST type Fiber ports. CNet media converters are hybrid-networking devices compliant to IEEE 802.3 and 802.3u standards.

KEY FEATURES

- TP Port supports Auto-negotiation and Auto-MDI-X
- Operates at Maximum Packet Filtering and Forwarding Rate
- TP Port:10/100Mbps Full-/Half-duplex
- Fiber Port: 100Mbps Full-/Half-duplex
- Interoperable with 10BASE-TX, and 100BASE-FX Hubs or Switches



SPECIFICATIONS

Product Name	10/100Mbps TP to 100Base-FX Media Converter, ST Type/ Multi-Mode/ 2KM
Model Name	CFC-20TM
Fiber Mode	Multi-Mode
Wave Length	1310nm
Fiber Cable	62.5/125µm
Fiber Cable Distance	2KM
Fiber Connector	ST Type
TP Ports	RJ-45 phone-type
LED Indicators	FX: LINK/ACT FX: FDX/COL TP: LINK.ACT TP: 100
Power Adapter	External DC5V, 2A
Environment	Operating Temperature: -20° ~ 70° C (-4° ~ 158° F) Storage Temperature: -40° ~ 80° C (-40° ~ 176° F) Humidity: 10% ~ 90% Non-condensing
Certifications	CE, FCC
Dimensions	94 x 70.3 x 26.2 mm (3.7 x 2.77 x 1.03 inches)

ORDERING INFORMATION

Model	Description
CFC-20TM (A)	10/100Mbps TP to 100Base-FX Media Converter, ST Type/ Multi-Mode/ 2KM